


# 6F6 6F6-G 6F6-GT

## POWER PENTODE

Metal type 6F6 and glass octal types 6F6-G and 6F6-GT used in the audio output stage of ac receivers. Tubes are capable of large power output with relatively small input voltage.



Outlines 6, 42 and 26, respectively, **OUTLINES SECTION**. Type 6F6-GT may be supplied with pin No.1 omitted. Tubes require octal socket and may be mounted in any position. It is especially important that these tubes, like other power-handling tubes, be adequately ventilated. Types 6F6-G and 6F6-GT are used principally for renewal purposes.

|                             |     |        |
|-----------------------------|-----|--------|
| HEATER VOLTAGE (AC/DC)..... | 6.3 | volts  |
| HEATER CURRENT.....         | 0.7 | ampere |

### CLASS A<sub>1</sub> AMPLIFIER

#### Maximum Ratings:

|  | <i>Pentode Connection</i> | <i>Triode Connection*</i> |       |
|--|---------------------------|---------------------------|-------|
| PLATE VOLTAGE.....                           | 375 max                   | 350 max                   | volts |
| GRID-NO.2 (SCREEN-GRID) VOLTAGE.....         | 285 max                   | -                         | volts |
| PLATE DISSIPATION.....                       | 11 max                    | 10 max                    | watts |
| GRID-NO.2 INPUT.....                         | 3.75 max                  | -                         | watts |
| <b>PEAK HEATER-CATHODE VOLTAGE:</b>          |                           |                           |       |
| Heater negative with respect to cathode..... | 90 max                    | 90 max                    | volts |
| Heater positive with respect to cathode..... | 90 max                    | 90 max                    | volts |

#### Typical Operation:

|                                       | <i>Pentode Connection</i> |       | <i>Triode Connection*</i> |          |
|---------------------------------------|---------------------------|-------|---------------------------|----------|
| Plate Voltage.....                    | 250                       | 285   | 250                       | volts    |
| Grid-No.2 Voltage.....                | 250                       | 285   | -                         | volts    |
| Grid-No.1 (Control-Grid) Voltage..... | -16.5                     | -20   | -20                       | volts    |
| Peak AF Grid-No.1 Voltage.....        | 16.5                      | 20    | 20                        | volts    |
| Zero-Signal Plate Current.....        | 34                        | 38    | 31                        | ma       |
| Maximum-Signal Plate Current.....     | 36                        | 40    | 34                        | ma       |
| Zero-Signal Grid-No.2 Current.....    | 6.5                       | 7     | -                         | ma       |
| Maximum-Signal Grid-No.2 Current..... | 10.5                      | 13    | -                         | ma       |
| Amplification Factor.....             | -                         | -     | 6.8                       |          |
| Plate Resistance (Approx.).....       | 80000                     | 78000 | 2600                      | ohms     |
| Transconductance.....                 | 2500                      | 2550  | 2600                      | μmhos    |
| Load Resistance.....                  | 7000                      | 7000  | 4000                      | ohms     |
| Total Harmonic Distortion.....        | 8                         | 9     | 6.5                       | per cent |
| Maximum-Signal Power Output.....      | 3.2                       | 4.8   | 0.85                      | watts    |

### PUSH-PULL CLASS A<sub>1</sub> AMPLIFIER

#### Maximum Ratings:

(Same as for class A<sub>1</sub> amplifier)

#### Typical Operation (Values are for two tubes):

|   |       |          |
|---|-------|----------|
| Plate Voltage.....                              | 315   | volts    |
| Grid-No.2 Voltage.....                          | 285   | volts    |
| Grid-No.1 (Control-Grid) Voltage.....           | -24   | volts    |
| Peak AF Grid-No.1-to-Grid-No.1 Voltage.....     | 48    | volts    |
| Zero-Signal Plate Current.....                  | 62    | ma       |
| Maximum-Signal Plate Current.....               | 80    | ma       |
| Zero-Signal Grid-No.2 Current.....              | 12    | ma       |
| Maximum-Signal Grid-No.2 Current.....           | 19.5  | ma       |
| Effective Load Resistance (Plate-to-plate)..... | 10000 | ohms     |
| Total Harmonic Distortion.....                  | 4     | per cent |
| Maximum-Signal Power Output.....                | 11    | watts    |

#### Maximum Circuit Values:

##### Grid-No.1 Circuit Resistance:

|                                 |         |        |
|---------------------------------|---------|--------|
| For fixed-bias operation.....   | 0.1 max | megohm |
| For cathode-bias operation..... | 0.5 max | megohm |

\* Grid No.2 connected to plate.